

# Errata for the HP Integrity rx2600 Video Update



October 2003 (First Edition)  
Part Number 5990-6812  
Version: 1.00 DC-10/3/03

© 2003 Hewlett-Packard Development Company, L.P.

Hewlett-Packard Company shall not be liable for technical or editorial errors or omissions contained herein. The information in this document is provided "as is" without warranty of any kind and is subject to change without notice. The warranties for HP products are set forth in the express limited warranty statements accompanying such products. Nothing herein should be construed as constituting an additional warranty.

Confidential computer software. Valid license from HP required for possession, use or copying. Consistent with FAR 12.211 and 12.212, Commercial Computer Software, Computer Software Documentation, and Technical Data for Commercial Items are licensed to the U.S. Government under vendor's standard commercial license.

64-bit Microsoft Windows on an Hp Integrity Superdome README

October 2003 (First Edition)

Part Number 5990-6812

---

# Contents

<b>HP Integrity rx2600 Video Resolution Limitation in Microsoft® Windows®.....</b>	<b>5</b>
Installation Instructions.....	5



---

# HP Integrity rx2600 Video Resolution Limitation in Microsoft® Windows®

Some HP Integrity rx2600 servers may have a limitation on their VGA resolution settings. This limitation restricts customers to a resolution of 640 x 480. The update is provided on the CD-ROM, part number: 5013-1135, which will allow the HP Integrity rx2600 customers to remove the video limitation. This update must be manually installed, only once, after successfully installing the operating system.

**IMPORTANT:** If for any reason the operating system is re-installed, the update must be re-run after reinstallation to enable resolutions greater than 640 x 480.

## Installation Instructions

After completion of the Windows operating system manual installation or mini-setup (mini-setup applies to operating system preload systems only) follow the steps below:

**NOTE:** Completion of the manual installation or mini-setup means that you have logged into the Windows desktop.

1. Insert the CD-ROM into the drive.
2. Restart the server.
3. From the EFI Boot Manager menu, select **EFI Shell**.
4. The update will run automatically.
5. When prompted to select “q” to quit or any other key to continue, select any key other than “q”.

**NOTE:** This patch copies two files to the EFI partition: a patched EFI driver that resolves the resolution restriction and a script that loads this EFI driver on system boot. Hitting “q” to quit the patch process does not abort the patch, it just prevents the script from running until a system reboot is executed.

6. The following message will be displayed: **ECI Video enabled** and you will be returned to an EFI prompt.
7. Type `exit` to return to the EFI Boot Manager Menu.
8. At this time, you may boot your server to Windows and change your resolution.

**IMPORTANT:** If you attempt to run Windows in a resolution higher than 640 x 480 without first installing this update, your machine will halt. The workaround for this condition is to install this update.