



The Security Division of EMC

RSA enVision Device Configuration

Last Modified: April 18, 2007

Device Product Information	
Vendor	HP
Device	UX
Supported Versions/Platforms	11.X/NA
enVision Product Information	
Device Type	hpux, 31
Collection method	Syslog
Device Class.Subclass	Host.UNIX
Service	None

Device Configuration – HP UX

To configure HP UX to work with enVision:

1. Turn on debugging and logging:
 - a. Open the `/etc/inetd.conf` file in a text editor.
 - b. Add `-d -l` to the `ftp` line: `/usr/sbin/ftpd -d -l`
 - c. Save the file. Close the text editor.
2. Log all messages of debug level or higher:
 - a. Open the `/etc/syslog.conf` file in a text editor.
 - b. Add the following line, where `xxx.xxx.xx.xxx` is the address for the syslog server:
`*.debug @xxx.xxx.xxx.xxx`
Important! Insert a **TAB** space between `debug` and `@xxx.xxx.xxx.xxx`.
 - c. Save the file. Close the text editor.
3. To indicate to the `inetd` daemon to read the configuration files, type `inetd -c` and press **ENTER**.
4. To start the `inetd` demon in logging mode, type `inetd -l` and press **ENTER**.
Note: Start `inetd` automatically with logging by placing a `-l` flag in the `/sbin/init.d/inetd` file where the `inetd` is being started.