

## **Cisco 1841 Router**

```
interface FastEthernet0/0
description NABUA LAN
ip address 192.168.2.3 255.255.255.0 secondary
ip address 192.168.0.9 255.255.255.0
no ip redirects
no ip unreachable
no ip proxy-arp
ip route-cache flow
duplex auto
speed auto
no mop enabled
!
interface FastEthernet0/1
ip address 192.168.3.1 255.255.255.0
no ip redirects
no ip unreachable
no ip proxy-arp
ip route-cache flow
duplex auto
speed auto
no mop enabled
!
interface FastEthernet0/1.2
encapsulation dot1Q 2
ip address 192.168.50.1 255.255.254.0
no snmp trap link-status
```

```
no cdp enable
!
interface FastEthernet0/1.3
encapsulation dot1Q 3
ip address 192.168.4.1 255.255.255.0
no snmp trap link-status
no cdp enable
!
interface FastEthernet0/1.4
encapsulation dot1Q 4
ip address 192.168.5.1 255.255.255.0
no snmp trap link-status
no cdp enable
!
interface Serial0/0/0
description LINK TO RRRT
ip address 192.168.1.1 255.255.255.252
no ip redirects
no ip unreachable
no ip proxy-arp
ip route-cache flow
!
ip classless
ip route 0.0.0.0 0.0.0.0 192.168.0.1
ip route 192.168.9.0 255.255.255.0 192.168.1.2
!
ip http server
```

```
ip http authentication local
ip http timeout-policy idle 60 life 86400 requests 10000
!
logging trap debugging
snmp-server community SUS2006 RO
no cdp run
!
control-plane
!
banner login ^CAuthorized access only!
Disconnect IMMEDIATELY if you are not an authorized user!^C
!
line con 0
login local
transport output telnet
line aux 0
login local
transport output telnet
line vty 0 4
privilege level 15
login local
transport input telnet
line vty 5 15
privilege level 15
login local
transport input telnet
!
```

```
scheduler allocate 4000 1000
```

```
end
```

### **HP 4204vl**

Running configuration:

```
; J8770A Configuration Editor; Created on release #L.10.23
```

```
hostname "ProCurve Switch 4204vl"
```

```
module 1 type J8768A
```

```
module 2 type J9033A
```

```
interface A7
```

```
    lacp Passive
```

```
exit
```

```
interface A8
```

```
    lacp Passive
```

```
exit
```

```
trunk A1-A2 Trk1 Trunk
```

```
trunk A3-A4 Trk2 Trunk
```

```
trunk A5-A6 Trk3 Trunk
```

```
ip default-gateway 192.168.3.1
```

```
snmp-server community "public" Unrestricted
```

```
vlan 1
```

```
    name "MANGMNT-LAN"
```

untagged A7-A24,B1-B19,B21-B24

ip address 192.168.3.8 255.255.255.0

tagged B20,Trk1-Trk3

exit

vlan 2

name "VOIP"

no ip address

tagged B20,Trk1-Trk3

voice

exit

vlan 3

name "CLIENT"

no ip address

tagged B20,Trk1-Trk3

exit

vlan 4

name "SERVER"

no ip address

tagged B20,Trk1-Trk3

exit

spanning-tree

spanning-tree Trk1 priority 4

spanning-tree Trk2 priority 4

spanning-tree Trk3 priority 4

spanning-tree priority 1